

# **Data Monitor** KS 3005

TFT display 5,5"

Measurement data acquisition from 250 ms

3, 6, or 12 universal 16-bit inputs; Class 0,2 %

**Channel visualization in groups** 

Storage medium: Compact Flash or 3.5-inch diskette

RS 232 or RS 485 interface for configuration and as Modbus master or Modbus slave

The KS 3005 offers 4 visualization

tain up to 6 channels.

displays can be activated.

2

0.500

1

0.0

10.0 10.0 10.7

groups, whereby every group can con-

Within a visualization group, different

1

3

15.0 15.0 27.0

**Ethernet interface** 

 $\bigcirc$ 

5

0.0 28.0 6

5.0

**N.9** 

27h 1/16

A

5.0

1.0

Mathematical functions in realtime

Front protection mode IP 65

#### **GENERAL**

The Data Monitor KS 3005 is a freely configurable, microprocessor-controlled device for measurement, storage, visualization, monitoring, documenting, and evaluating measurement data. Various versions are available, with 3, 6, or 12 universal inputs. Via a Modbus link, the unit can be expanded with 12 additional channels

Measured data are buffered in the internal memory, from where they can be exported to a Compact Flash card or diskette. By means of a PC-based evaluation program, the measurement data can be archived for subsequent analysis.

The device has been designed for industrial use, and apart from numerous extra functions. It offers the latest communication possibilities. For example, via the Ethernet interface the KS 3005 can be configured completely, and the integrated web server permits convenient monitoring. E-mail messaging and FTP client and server functions put a finishing touch to the Ethernet communication concept.

In its immediate automation environment, the KS 3005 is also very communicative: a serial interface with Modbus function can be used for slave or master operation.

Another highly important link to the process is the 5,5-inch (140 mm) TFT display with a resolution of 320 x 240 pixels. The display provides excellent readability even at wide angles.

Measurement values can be displayed either as trend curves or bargraphs in horizontal or vertical direction; a numeric display is also possible.





Bargraph display

-0.500 VJ

0.000

an.Abtastdaten (01 los.Daten (000∕ ≊ortdaten (00 otastdaten :●D	/58) : Feb.09 17:09 400) : /40) : isplaudaten	9:39 REL. 0:00
Startzeit	Stoppzeit	Daten Faktor
Feb. 10 10:05:05 Feb. 10 05:45:10 Feb. 10 05:45:10 Feb. 10 05:05 Feb. 10 05:05 Feb. 10 05:05 Feb. 10 05:05 Feb. 10 05:05 Feb. 10 05:51:0 Feb. 10 05:25 Feb. 10 17:245 Feb. 09 17:245	2 Feb.10 10:10:46 2 Feb.10 09:54:24 2 Feb.10 09:44332 2 Feb.10 09:44332 2 Feb.10 09:44332 2 Feb.10 09:4436 2 Feb.10 09:4436 5 Feb.10 09:42100 5 Feb.10 09:42100 5 Feb.10 09:42104 2 Feb.10 09:42104 4 Feb.10 09:23154 4 Feb.10 09:23154 5 Feb.10 91755140	323 Rotasten 165 Auto-Spei. 250 Storp 680 Auto-Spei. 680 Auto-Spei. 267 Auto-Spei. 30 Storp 680 Auto-Spei. 117 Storp 680 Auto-Spei. 326 Rocshalten 680 Auto-Spei.

#### Event list

From the vertical and horizontal displays, it is also possible to call a historic display of the data stored in the memory.

Digital display The KS 3005 features a group manager,

with which the different input signals can be assigned freely to a visualization aroup.

Any input signal can be assigned to several groups. Grouping the inputs helps to improve transparency, and also permits the use of different parameters for every signal within a group.

#### **TECHNICAL DATA**

# ANALOG INPUTS

#### General

Programmable sensor type and measurement range.

Within a measurement range, span start and end can be configured freely. Galvanic isolation between inputs up to 50 VDC

#### Scanning cycle

3 inputs from 250 ms upwards 6 or 12 inputs from 1 s upwards Resolution: 16 bits

#### Thermocouples

Туре	Measurement range
R	01760 °C
S	0 1760 °C
В	01820 °C
К	-200 1370 °C
E	-200800 °C
J	-200 1100 °C
Т	-200 400 °C
Ν	01300 °C
W	02315 °C
L	-200 900 °C
U	-200 400 °C
WRe	02400 °C

#### Resistance thermometers

Туре	Measurement range	
Pt 100	-200 600 °C	
Jpt 100	-200 550 °C	

For all thermocouples and resistance thermometers, the smallest display span is 0,1 °C.

#### Direct voltage

Voltages can be measured and displayed in the following ranges:

Measurement range	Resolution
-20 20 mV	10 μV
-60 60 mV	10 μV
-200 200 mV	100 µV
-2 2 V	1 mV
-6 6 V	1 mV
-20 20 V	10 mV
-50 50 V	10mV

#### Direct current

Currents are measured by means of an external shunt. Therefore, the ranges specified above for direct voltage are used.

Accuracy and display

The errors specified in the table are referred to the following conditions: Humidity:  $55\% \pm 10\%$ Temperature:  $23 \ ^{\circ}C \pm 2^{\circ}C$ Supply voltage:  $180 \text{ to } 250 \text{ V} \text{ at } 50 \text{ Hz} \pm 1\%$ 

The Data Monitor must have been in operation for at least 30 minutes (warm-up time)

Туре	Error
R	± 3,7 °C with 0100 °C ± 1,5 °C with 100300 °C
S	± 3,7 °C with 0100 °C ± 1,5 °C with 100300 °C
В	± 2 °C with 400600 °C
К	+ 1 °C with -200100 °C
E	+ 0,7 °C with -200100 °C
J	+ 0,7 °C with -200100 °C
Т	+ 0,7 °C with -200100 °C
Ν	+ 0,7 °C
W	+ 1 °C
L	+ 0,5 °C
U	+ 0,7 °C with -200100 °C
WRe	+ 1 °C
Pt 100	+ 0,3 °C
Jpt 100	+ 0,3 °C

An error of +/-0,1% + 2 digits applies for all voltage measurements (50V + 3 digits).

# **DISPLAY / OPERATION**

TFT colour display Screen diagonal: 5,5 inches Resolution: 320 x 240 pixels Automatic switch-off function Selectable operating languages: German, English, French, Italy and Spain.

The KS 3005 is operated via softkeys in the front panel or via a network (Ethernet / RS 232 / RS 485 (Options))

Unit configuration is also done via the front panel keys, network (Option) or via the storage medium (Option).

# DATA STORAGE

Internal data storage: 1,2 MB Flash Optional external storage:

- Floppy disk, 1,44 MB, 3.5-inch
- Compact Flash, 32 MB up to 512 MB

Data storage can be initiated either manually via softkeys or external input (Option) or automatically.

# POWER SUPPLY

Supply voltage: 100..240 VAC Frequency: 50/60 Hz (automatic detection) Nominal power consumption: 14 VA at 100 VAC; 22 VA at 240 VAC Max. power consumption 24 VA at 100 VAC; 35 VA at 240 VAC

Option. rated supply voltage: 24 V DC/AC Op. supply voltage range:21.6 to 26.4 V DC/AC Max.. power consumption 24 V DC 17 W 24 VAC(50/60Hz 30VA

# **ENVIRONMENTAL CONDITIONS**

Normal operating conditions: Temperature: 0 ..50 °C (with floppy disk: 0..40 °C) Humidity: 20...80% at 0...40°C 10...40% at 40...50°C Vibration: 10...60 Hz; 0,2 m/s<sup>2</sup> Warm-up time: 30 minutes

# STORAGE CONDITIONS

Temperature: -25...60°C Humidity: 5...95%, no condensation

#### **CONFORMITY / SAFETY**

#### **CE** marking

The device complies with the conformity regulations

#### Safety

CSA22.2 No. 1010-1, UL61010B-B (CSA NRTL/C) EN 61010-1

#### ЕМС

EN 61326 EN 55011 Class A EN 61000-3-2 EN 61000-3-3

#### **OPTIONS**

# ALARM OUTPUTS

Depending on version, the unit has 2, 4 or 6 alarm outputs. The outputs are relay contacts rated for 250 VAC (50/60 Hz), 3 A.

# SERIAL INTERFACES

Depending on version, the Data Monitor can be fitted with an RS 485/422-A or RS 232 interface.

The interface can be used for configuration by means of the recorder software, or as a Modbus interface.

With Modbus operation, the unit can be configured as Modbus master (this requires the 'Mathematics' option) or as Modbus slave. When configured as Modbus master, up to twelve additional external channels can be read, whereby these channels only occupy one mathematics channel.

# ETHERNET INTERFACE

The Ethernet interface offers the following protocols and functions:

- SMTP, HTTP1.0, FTP, TCP, UDP, IP, ARP, ICMP
- E-mail function for sending alarm messages and data.
- Web server function for displaying a standard operating interface on a conventional browser.
- FTP client function for automatic data transfer from the Data Monitor to an FTP server.
- FTP server function for data transfer via an FTP client.

# MATHEMATICS FUNCTION

The 'Mathematics' function enables up to twelve additional channels to be defined.

The functions include general arithmetic calculations, logic operations, statistical functions, reporting functions, and triggering of automatic sequences.

# **REMOTE OPERATION**

Depending on version, the Data Monitor can be fitted with 5 or 8 remote control inputs. These inputs are used to trigger different functions in the unit, e.g.:

- Start / Stop of recording
- Start / Stop of calculations
- Time synchronization
- Reset for mathematical functions

- Manual data recording
- Display of predefined texts
- Alarm acknowledgement
- Screen dump

# PULSE INPUTS

The 'Pulse inputs' option comprises 3 pulse inputs, 5 remote control inputs (see Remote operation), as well as the 'Mathematics' function (see Mathematics function).

Specifications of the pulse inputs

- Max. pulse frequency: 100 Hz
- Min. pulse length: 5 ms
- Max. voltage: 30 VDC

Pulse counting can be done during a defined period or as a total sum.

# **BUFFER OVERFLOW**

The 'buffer overflow' signal is available as a relay output rated at 250 VAC, 3 A. The signal is triggered at a specified time during manual recording, or automatically, when the storage medium reaches 90% of its capacity.

# PT 1000

Expansion of the input channels with the linearization for Pt 1000 resistance thermometers.

Туре	Measurement range
Pt 1000	-200 600 °C

Sensor current: 0,16 mA Error: ± 0,2%

# ISOLATED RTD

The signals A, B, and b are galvanically isolated. This option is standard in the 3-channel version.

# APPLICATION SOFTWARE

A license for the application software is included with every unit that is supplied with an interface or storage medium.

The software runs under Windows 98/Me/NT4.0/2000/XP, and serves for the unit's configuration as well as the evaluation of the stored data.

Configuration is done via a storage medium or via a direct link (interface). Primarily, the evaluating software supports the following functions:

- Display of the channels in groups as diagram, text display, and in reports
- Statistical evaluations
- Database function
- Data export as ASCII file
- Printout of the displayed data

#### GENERAL

# **PROTECTION MODE**

To EN 60529 Front IP 65, rear IP 20

# HOUSING

Sheet steel housing for mounting in a panel cutout. Panel fixing elements to DIN. *Weight*: 2,5kg



Order no	9407-31 x	- X	X	Х	Х	
	<b></b>	•	▲	♠	1	× 7
Inputs and interface						
3 channels	1					
3 Channels + KS 232 ^1	2					
3 channels + KS 485/422-A "I	3					
o channels 6 channolo - PS 222 *1	4 E					
6  channels + RS 232  T	5					
12 abannolo	0					
12 channels + PS 222 *1	/ 0					
12 channels + RS $485/422-\Delta *1$	o q					
Storage medium and Ethernet	J		t.	t.		
without storage medium and without Ethernot			T.			
Diskotto (EDD 1 44 MB, 3 5-inch)		1				
Compact Flash (32MB)		2				
Ethernet without storage medium		3				
Ethernet + diskette (EDD 1 44MB 3 5 inch)		4				
Ethernet + Compact Flash (32MB) (recommended feature	resl	5				
Alarm outputs	, ,	Ū	t.	t.		
without alarms			0			
2 alarm outputs			1			
4 alarm outputs			2			
6 alarm outputs			3			
Output for buffer overflow signal			4			
2 alarm outputs + buffer overflow signal			5			
4 alarm outputs + buffer overflow signal			6			
Options 1				t		
without Options 1				0		
Mathematics *1				1		
8 remote control inputs				2		
Mathematics + 8 remote control inputs	×			3		
Mathematics + 3 pulse inputs + 5 remote control inputs	*2	_		4	_	_
Options 2						
without Options 2					0	
Pt 1000 connection Calv isolation 2 nin RTD operaization					2	(
Galv. isolation 3-pin RTD energization Galv. isolation 3-pin RTD energization + Pt 1000					3	
Options 3						
without Options 3						
Portable Kit						:
Power supply 24 Volt						
Portable Kit + Power supply 24 V						4

#### ACCESSORIES X

# SHUNT RESISTORS

Order no.	Туре
9407-310-80011	250 ohms ± 0,1%
9407-310-80021	100 ohms ± 0,1%
4012-151-57322	50 ohms ± 0,1%
9407-310-80031	10 ohms ± 0,1%

# **APPLICATION SOFTWARE**

A license for the application software is included with every unit that is supplied with an interface or storage medium.

Order no.	Туре
9407-310-70011	REC standard

# **OPERATING INSTRUCTIONS**

One operating manual is supplied with the unit.

Standard operating instructions

Order no.	Language
9499 040 75418	German
9499 040 75432	English

#### Interface description

Order no.	Language
9499 040 75618	German
9499 040 75611	English

# Software operation

Order no.	Language
9499 040 75518	German
9499 040 75511	English

Remarks

\*1 If the KS 3005 is to be operated as a Modbus master, the option 'Mathematics' must be selected. \*2 If the 3 pulse inputs are selected, only max. 4 alarm outputs are possible.



#### **PMA** Prozess- und Maschinen- Automation GmbH P.O. Box 31 02 29 D-34058 Kassel Tel.: +49 - 561- 505 1307 Fax: +49 - 561- 505 1710 E-mail: mailbox@pma-online.de Internet: http://www.pma-online.de

Your local representative: